

ZLE series

■ Standard Rating

WV (Vdc)	Cap (µF)	Size ØxL (mm)	Tanδ	Ripple Current (mA _{RMS} /105°C, 120Hz)	Code No
6.3	33	5 x 5	0.22	100	ZLE6R3□330D05CS□□□
	47	5 x 5	0.22	100	ZLE6R3□470D05CS□□□
	68	6.3 x 5	0.22	140	ZLE6R3□680E05CS□□□
	100	6.3 x 5	0.22	140	ZLE6R3□101E05CS□□□
10	33	5 x 5	0.20	100	ZLE010□330D05CS□□□
	47	6.3 x 5	0.20	100	ZLE010□470E05CS□□□
	68	6.3 x 5	0.20	140	ZLE010□680E05CS□□□
	100	6.3 x 5	0.20	140	ZLE010□101E05CS□□□
16	15	5 x 5	0.18	100	ZLE016□150D05CS□□□
	22	5 x 5	0.18	100	ZLE016□220D05CS□□□
	33	6.3 x 5	0.18	140	ZLE016□330E05CS□□□
	47	6.3 x 5	0.18	140	ZLE016□470E05CS□□□
25	10	5 x 5	0.14	100	ZLE025□100D05CS□□□
	15	5 x 5	0.14	100	ZLE025□150D05CS□□□
	22	5 x 5	0.14	100	ZLE025□220D05CS□□□
	33	6.3 x 5	0.14	140	ZLE025□330E05CS□□□
	47	6.3 x 5	0.14	140	ZLE025□470E05CS□□□
35	1.0	5 x 5	0.12	80	ZLE035□1R0D05CS□□□
	1.5	5 x 5	0.12	80	ZLE035□1R5D05CS□□□
	2.2	5 x 5	0.12	80	ZLE035□2R2D05CS□□□
	3.3	5 x 5	0.12	80	ZLE035□3R3D05CS□□□
	4.7	5 x 5	0.12	80	ZLE035□4R7D05CS□□□
	6.8	5 x 5	0.12	80	ZLE035□6R8D05CS□□□
	10	5 x 5	0.12	100	ZLE035□100D05CS□□□
	15	5 x 5	0.12	100	ZLE035□150D05CS□□□
	22	6.3 x 5	0.12	140	ZLE035□220E05CS□□□
33	6.3 x 5	0.12	140	ZLE035□330E05CS□□□	

■ Rated ripple current multipliers

Cap(µF) \ Freq.(Hz)	120	1k	10k	50k	100k
1 ~ 100	0.40	0.75	0.90	0.95	1.00